



Pack GOHead

1 GO Mono receiver • 1 GO Body bodypack transmitter
• 1 headband GO Head microphone

Code : 10001

EAN : 3662009012032

Technical data

GOMono receiver

- 16 UHF frequencies
- UHF Frequency range: 863-865 MHz
- The Diversity system ensures a perfect reception
- Adjustable Squelch to absorb interferences
- You can use up to 4 receivers at the same time (4 mic)
- Adjustable antennas (front)
- Average range in perfect conditions: 70m
- Balanced XLR outputs and unbalanced Jack output
- Use FREE-RACK to stack them in racks (optional)
- Dimensions: 130 x 36 x 92 mm

GOBody emitter

- Must be combined with a tie-clip or headband GO series microphone and a GO-MONO receiver
- High-quality electret microphone
- THD :
- Mini XLR input
- 2 impedance modes: line or micro
- Operates with 2x1.5V type AA batteries
- Must be combined with a tie-clip or headband GO series microphone and a GO-MONO receiver
- Dimensions : 237 x 58 mm

GOHead headband microphone

- Headband microphone only. Must be combined with a GO-BODY transmitter and a GO-MONO receiver
- Mini XLR connector
- Supplied with a microphone windshield and an adjustable headband
- Unidirectional electret
- Frequency response : 100 Hz at 16 kHz
- S/N : > 60 dB
- Impedance: 2.2 kOhms